



MR16-HO

MR16 BI Pin Replacement Lamp

Monochromatic 3, 4 or 5 LED array light source

The MR16-HO is a low voltage, monochromatic LED array light source utilizing MR16 2-pin connection. Simple to install, energy efficient and virtually maintenance-free, the MR16-HO offers various advantages over most other conventional and LED small light alternatives.



Technical Specifications

Standard*	in Red, Amber, Orange, Blue, Green, White (3K, 5K, 8K)
Input Voltage.....	12VAC or 24VDC
Must specify when ordering
Input Current.....	350mA
Number of LEDs.....	3, 4 or 5
LED 1.2W High Output.....	AllInGaP (Red, Amber)
	InGaN (Blue, Green, White)
Body.....	Standard MR-16 base
	GU 5.3 or GU 10
Connection.....	2 pin MR16

*Custom colors – special order

Key Features

- High-end visual excitement at a low-end operating cost – compared to conventional & LED alternatives
- Compact size and low voltage power requirement allows for easy integration into products and displays
- Long life – up to 100,000 hours
- Daisy chain multiple lamps to create a uniform display

Applications

- Spot and daisy-chained lighting applications
- Wide variety of accent and decorative lighting, especially architectural & entertainment features, retail, exhibit & display
- Popular uses: bar back, & uplighting bottles, water displays & splash, ice lighting, glass edge, exhibit & display, sales promotions, etc.
- OEM integration into products and displays



Additional information & details at www.bocaflasher.com

The most current information, including data sheets, schematics, product integration sheets, power & control information, and additional information on cables, accessories, and more are on the Boca website. For specific requirements, contact your Boca sales representative.

